

MAGEWELL

Pro Convert HDMI TX Technical Specifications

Copyright (c) 2011–2021 [Nanjing Magewell Electronics Co., Ltd.](http://www.magewell.com) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

HDMI, the HDMI logo and High-Definition Multimedia interface are trademarks or registered trademarks of HDMI Licensing LLC. NDI is trademark or registered trademark of NewTek Inc.

Revised 27/01/2021

Input Features

- Max video input: 2048x1200 60fps 4:4:4/4:2:2
- Input video at any format by custom EDID of input port
- Video formats: RGB, YUV BT.601/709/2020
- 8-channel HDMI-embedded audio
- HDMI interface: HDMI 1.4, DVI-D

NDI[®] Encoding Features

- Encoding Full NDI real-time stream at up to 2048x1200 60fps 4:2:2 8-bit.
- Output the same resolution as input or any custom resolution. Typical outputs include:
 - 2048x1080p/1920x1080p 23.98/24/25/29.97/30/50/59.94/60
 - 1920x1080i 25/29.97/30/50/59.94/60
 - 1280x720p 23.98/24/25/29.97/30/50/59.94/60/100/119.88/120
 - 720x480p/720x480i 59.94/60/119.88/120
 - 720x576p/720x576i 50/100
- Output frame rate same as the original, 1/2, 1/3 or 1/4 of input frame rate
- Encoding 2-channel NDI-embedded audio
- Support NDI 4.x

Web UI Management

- Provide comprehensive information regarding the device and input signals in real-time
- Allow to configure how an input is processed and encoded, including deinterlacing, EDID, up/down scaling, frame rate, aspect ratio, as well as the network connection
- Update firmware
- Support USB RNDIS/ECM
- Support IE/Edge/Firefox/Chrome/Safari/Opera web browsers
- Provide HTTP APIs

On-board Control Buttons

- 16 Position Rotary DIP Switch: set board-index from 0 to F

PTZ Control

- Control PTZ cameras using protocols of VISCA, Visca UDP, Visca UDP2rs232, PELCO-P and PELCO-D via NDI
- Mini-DIN-8 jack (shared with Tally light)

Network Interfaces

- 10/100/1000Mbps Ethernet
- IEEE 802.3af PoE

USB Interface

- USB2.0 Type B
 - 5V/2.1A power supply
 - USB RNDIS/ECM

Supported Products

- NDI Studio Monitor
- OBS
- vMix
- Any other NDI-enabled product

LED Indicators

- Status LEDs indicate:
 - Power supply: on/off
 - Input signal: locked/unlocked

Form Factor

- 100.95mm (L) x 60.2mm (W) x 23.3mm (H)

Accessories

- USB 2.0 A to B cable
- 5V/2.1A power adaptor
- Mini-DIN 8 breakout cable
- Tally light
- L-bracket

Screw Mounting Hole

- ¼–20 threaded hole

Power Consumption

- 5V max current: ~1.5A
- Max power consumption: ~6W

Working Environment

- Operating temperature: 0 to 40 deg C
- Storage temperature: –20 to 70 deg C
- Relative humidity: 5% to 90% non-condensing